

Overview

HP Engage One Prime I/O Hub



Models

HP Engage One Prime I/O Hub	4VW60AA/AT
HP Engage One Prime White I/O Hub	4VW66AA/AT

Service and Support

Three (3) year limited warranty with advance exchange when purchased from HP. Additional HP Care Pack Services options are available to extend warranty coverage.

Technical Specifications

General	Ports	<p>1 USB-C™ PD port dedicated for host platform (PD power source up to 15V/3A)</p> <p>1 USB-C™ PD port dedicated for peripheral (PD power source: 9V/3A, 5V/3A, 5V/0.9A)</p> <p>4 USB-A ports (USB 2.0)</p> <p>1 Powered USB port (12V) combined with 1 USB-A port (USB2.0)</p> <p>2 Powered RS232 ports (0/5/12V can be set in HP Engage One Prime OS setting menu)</p> <p>1 RJ12 port (24V/1A) for cash drawer</p> <p>1 RJ45 Ethernet port (10/100/1000)</p>
LED Behavior	<p>When host is connected</p> <p>When host is removed</p> <p>Power on without host</p> <p>When error occurs</p>	<p>On/off with host is on/off; breathing with host is breathing</p> <p>On for 15 seconds then breathing</p> <p>On for 15 seconds then breathing</p> <p>Blinking</p>
Weight		1.08lb (490g)
Dimension		55mm(W) x 220mm(L) x 26.4mm(H) (2.17inch x 8.66inch x 1.04inch)
Power adaptor requirement	Rated power	120W, 19.50V +/-5%, 6.15A(HP 4.5mm Barrel type)
Temperature	<p>Operating</p> <p>Non-operating</p>	<p>32~95 °F (0~35 °C)</p> <p>-22~149 °F (-30~+65 °C)</p>
Relative humidity	Operating	10%~90% RH,
Altitude	<p>Operating</p> <p>Non-operating</p>	<p>10000 ft. (3048 m)</p> <p>30000 ft. (9144 m)</p>
Network manageability	Wake On Lan (WoL) is not supported with HP Engage One Prime or HP Engage One Prime Plus	
Power Delivery (PD)	Support HP proprietary dynamic PD configuration when connecting with HP Engage One Prime or HP Engage One Prime Plus	
Option Kit Contents	HP Engage One Prime I/O Hub, Documentation	

Summary of Changes

Date of change:	Version History:		Description of change:
	From v1 to v2		

© Copyright 2018 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.